


ch.	name	DMX values																																					
		0	16	32	48	64	80	96	112	128	144	160	176	192	208	224	240	255																					
1)	Colours Master	M-C-Y		BLACK			WHITE			M	B	C	G	Y	R	Rainbow																							
2)	Colours Speed	max	(min)																							(max)													
3)	Reflector Speed	F I X	(min)								CW Rotation								(max)		F I X	(min)								CCW Rotation								(max)	
4)	Lamp & Reset	Hy..	Lamp Off				Hysteresis				Lamp On																												
5)	Shutter	[Shutter bar]																																					
6)	M	[M color bar]																																					
7)	C	[C color bar]																																					
8)	Y	[Y color bar]																																					
9)	Pan 8 bit	-270°								0°								+270°																					
10)	Tilt 8 bit	-131°								0°								131°																					
11)	Pan 16 bit	-1°								0°								+1°																					
12)	Tilt 16 bit	-1/2°								0°								+1/2°																					
13)	Pan speed adj.*	m a x	slow								Smooth Movement								fast																				
14)	Tilt speed adj.*	m a x	slow								Smooth Movement								fast																				
		0	16	32	48	64	80	96	112	128	144	160	176	192	208	224	240	255																					

* 0-7 = full speed/high torque hard movement; 8-255 = smooth movement